

Technical Specifications

Power Supply	6...30VDC SELV or 2x 1.5V AAA-battery
Power Consumption	typ. 87mW, max. 119mW
Total Power Loss	max. 119mW
Battery Lifetime	approx. 2 years
Safety Rating	IP30
Ambient Temperature SELV Powered	-20...70°C / -4...158°F
Ambient Temperature Battery Powered	-20...54°C / -4...129°F
Humidity	95% r.H. (non condensing)
Radio Frequency	868MHz (SRD Band Europe), 915MHz (ISM Band Region 2) max. Power 3.16mW
Dimensions	90x90x16mm / 3.54x3.54x0.63" (LxWxH)
Maintenance & Cleaning	This device is free of main- tenance and may only be cleaned with a dry cloth.

LOXONE

No Gimmicks.
Real Smart Homes.

Need Help?

loxone.com/support

Loxone Electronics GmbH
Smart Home 1
4154 Kollerschlag
Austria

loxone.com




LOXONE

Touch Pure Air

Part No.: 100399 (white)

Part No.: 100400 (anthracite)



About the product

The Loxone Touch Pure has five touch zones, which can be configured according to your needs. The large central touch zone is ideal for controlling lighting, whilst the corner zones are handy for controlling music and blinds, for example.

Features

- 5 touch buttons
- Temperature & Humidity sensor
- Optional click feedback
- Orientation LED light

Installation

Install the mounting frame on the desired installation place. Power up the device with the provided battery and pair it with your Miniserver in Loxone Config. To finish the installation attach the Loxone Touch on the mounting frame.

Information

Contains FCC ID: COR-ZWIR4512AC1

This device complies with part 15 of the FCC Rules.

Operation is subject to the following two conditions:

1. This device may not cause harmful interference
2. This device must accept any interference received, including interference that may cause undesired operation

This folder is a part of the product!



For additional information, declaration of conformity, visit www.loxone.com/help/touch-pure-air

